



Did you know that you can choose which charger works best for your patient at the time of hearing aid order?

Charger Compatibility

Chargers		Integrated Xperience (IX) and Augmented Xperience (AX)						
	Pure Charge&Go Portable Charger*	Pure Charge&Go Charger	Pure Charge&Go Dry&Clean Charger	Insio Charge&Go AX Charger	Styletto AX Charger*	Styletto AX Dry&Clean Charger	Charging Pad ¹	Clinic Multicharger
Type of charger	Galvanic	Galvanic	Galvanic	MR Inductive	Galvanic	Galvanic	–	Galvanic
Part number	10993118	10996345	10991650	10997503	21003216	21007593	PN 10245297	PN 21026076
Cord connection	USB-C PN 21023081	Attached	USB-C PN 21023081	USB-C PN 21023081	USB-C PN 21023081	USB-C PN 21023081		Attached
Wear time without streaming	39h	39h	39h	24h	20h	20h		39h
Wear time with streaming	36h	36h	36h	20h	17h	17h		36h
Charge time	4h	4h	4h	4h	4h	4h		4h
Quick charge time	30m for 9h	30m for 9h	30m for 9h	30m for 4h	30m for 5.5h	30m for 5.5h		30m for 9h
Portable charger extra charges	3	N/A	N/A	N/A	4	N/A		N/A
Hearing Aids								
RIC	Pure C&G IX/AX	*	•	•				•
	CROS Pure C&G IX/AX	*	•	•				•
	Styletto AX					*	•	•
	CROS Styletto AX					*	•	•
Custom	Insio C&G AX				•*			

¹ Optional Stand available for the portable chargers through accessories.

• Compatible

* Default (Recommended)

Please note – While the X hearing aids will work with the Inductive Charger I, the charger was not custom made for their shape. Please verify that the lights turn on when placing the hearing aid in the charger so that you can ensure proper placement.



signia

Charger Compatibility

Chargers	Xperience (X)								
	Inductive Charger I	Inductive Charger II	Styletto X Charger	Dry&Clean Charger P X	Motion C&G Charger P X	Dry&Clean Charger SP X	Motion C&G Charger SP X	Charging Pad ¹	Clinic Multicharger
Type of charger	Inductive	Inductive	Galvanic	Galvanic	Galvanic	Galvanic	Galvanic	–	Galvanic
Part number	10948199	10966942	10972015	10991638	10996335	10991644	10996340	PN 10245297	PN 21026076



Cord connection	micro USB	micro USB	USB-C	USB-C	Attached	USB-C	Attached		Attached
Wear time without streaming		24h	19h	30h	30h	61h	61h		39h
Wear time with streaming		21h	16h	27h	27h	57h	57h		36h
Charge time		4h	4h	4h	4h	4h	4h		4h
Quick charge time		30m for 6h	30m for 5h	30m for 7h	30m for 7h	30m for 4h	30m for 4h		30m for 9h
Portable charger extra charges		N/A	3	N/A	N/A	N/A	N/A		N/A

Hearing Aids										
RIC	Pure C&G X	•	•*							
	CROS Pure C&G X	•	•*							
	Styletto X			•*				•		
	Pure C&G Nx	•	•*							
BTE	Motion C&G X	•	*							
	Motion C&G P X				•*	•			•	
	Motion C&G SP X						•*	•	•	

All rechargeable hearing aids are shipped from Signia in the off position. To turn devices on:

- Pure and Motion Products – press and hold button on hearing aids for three seconds or insert and remove from the charger (charger must have power source)
- Styletto and Active Products – Place hearing aids in charger and do one of the following:
 - Press and hold button on charger for five seconds (charger must have a charge)
 - Plug charger into power source
 - Place charger on a Qi Pad

Signia is a registered trademark of WSAUD A/S. SIV-17633-22

Be
Brilliant™